

H SERIES

Lever and Push Operation Type Switch Tact Switch



Features

- The control unit provides both momentary operation by lever and center push operation.
- Using a single knob enables compound actions with simple operations.
- Reflow solderable.

Applications

- For the operation of telecommunication equipment such as mobile phones, etc.
- Compact, portable units such as camcoders, portable audios, car radios, etc.

Specification

Items		Standard
Operating temperature range		-30°C to +85°C
Electrical performance	Rating	10mA, 5V DC
	Output voltage	1V max. at 1mA 5V DC
	Contact resistance	100mW max.
	Lifetime	100,000 Cycles
Durability	Operating force	Lever portion 70 ± 40gf Push portion 200 ± 100gf
Mechanical performance	Travel	4-direction -25° -0° - +25°
		Push portion 0.85 ± 0.1mm

Diagram

No.	Dimensions	Circuit Diagram																																																
		Pad Layout																																																
1	<p>• TMHU28</p> <p>• TMHU29</p> <p>Code table</p> <table border="1"> <tr> <td></td> <td>25°)</td> <td>CW</td> <td>0°</td> <td>CCW</td> <td>25°)</td> </tr> <tr> <td>Angle</td> <td>(21.5°)</td> <td>(11°)</td> <td></td> <td>(11°)</td> <td>(21.5°)</td> </tr> <tr> <td>Terminal</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>①</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>②</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>③</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>④</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>⑤</td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> </table>		25°)	CW	0°	CCW	25°)	Angle	(21.5°)	(11°)		(11°)	(21.5°)	Terminal						①						②						③						④						⑤						
	25°)	CW	0°	CCW	25°)																																													
Angle	(21.5°)	(11°)		(11°)	(21.5°)																																													
Terminal																																																		
①																																																		
②																																																		
③																																																		
④																																																		
⑤																																																		